倍思包装设计稿件信息 Baseus

基本信息	产品型号	BPE45A		
	产品名称	倍思 优塔ioTa随行电户外移动电源 420W（美日规110V）冷松绿		
	产品方案编码			
	物料编码	1000056278	包装编码+版本号	PB3813Z-P0A0
	物料规格描述	说明书\悦声高白80G，单色印刷，骑马钉，160*190MM，8页16P		
	包装平面设计	Andy 李运成	包装结构设计	易婷

版本历史

版本	变更日期	变更描述
P0A0	2022.12.08	初始版本

包装审核区域责任划分 Baseus

产品相关	产品外观/参数/缝隙	产品经理/项目主管请在此处签名
	彩盒/说明书文案	
	执行标准/生产商信息	
认证相关	认证相关文案	认证工程师请在此处签名
	认证相关图标	
品质相关	法律法规相关文案	品质工程师请在此处签名
	警示语	
定制需求	定制渠道需求	定制代表请在此处签名
品类相关	产品功能/图标表达	品类策划/文案策划请在此处签名
	文案部分/翻译	
包装设计相关	产品条形码	包装设计师/组长/主管请在此处签名
	公司地址信息	
	文件基于最新量产版	
	包装设计规范	

温馨提示：请印刷供应商严格按照倍思的图纸印刷生产。如贵司有生产上的原因需要调整倍思图纸的字体、图形、颜色、刀模尺寸等，请必须通知倍思相关负责的包装设计师，并在征得包装设计师同意的情况下修改文档并发回存档。

切线 ——— 折线 - - - - 刀线图例

K

Baseus

Baseus

User Manual
取扱説明書

Baseus IoTa Series Portable Power Station 420W (US/JP 110V)
倍思 優塔IoTaエネルギーステーション携帯ポータブル電源420W（110V US/JP）

Thank you for purchasing Baseus IoTa Series Portable Power Station. (hereinafter referred to as Baseus Digital Portable Power Station). The information contained herein affects your safety and your legal rights and responsibilities. Read this manual carefully before using the Baseus Digital Portable Power Station. Failure to follow the instructions and warnings herein may result in serious injury to you or bystanders, or damage to your device or property. Shenzhen Baseus Technology Co. Ltd. reserves the right of final explanation for this document and all relevant documents relating to Baseus Digital Portable Power Station. Contents are subject to change without further notice.

感謝、優塔(IoTa)エネルギーステーション携帯ポータブル電源をご購入、当社デジタルエネルギー充電と放電をご購入いただきありがとうございます。本取扱説明書に記載されている内容は、お客様の安全上の利害関係および責任に関係しています。デジタルエネルギーステーション携帯ポータブル電源を使用する前に、本取扱説明書を注意深くお読みください。本書に記載されている指示や警告を遵守しないと、重大な人身傷害や、お客様または第三者の財産の損害、または機器や財産の損害を引き起こす可能性があります。本取扱説明書と当社デジタルエネルギー充電と放電またはすべての文書の最終的な解釈権は深セン市倍思科技有限公司に帰属します。内容は予告なく変更されることがあります。

By using this product, you hereby signify that you have read this document carefully and that you understand and agree to abide by the terms and conditions herein. You agree that you are solely responsible for your own conduct while using this product, and for any consequences thereof. You agree to use this product only for purposes that are authorized by this document, as well as by terms, procedures, practices, policies and guidelines Shenzhen Baseus Technology Co. Ltd. (Baseus Digital Portable Power Station).

本製品を使用する際に、当事者は当該文書をよく読み、すべての条項に同意を確認して理解し、当該製品の使用上の責任と、それによる結果を負担します。当事者は、本製品の使用に当たっては、すべての適用法令に従うことに同意します。本取扱説、本製品を含む当社デジタルエネルギー充電と放電に、これらの条件、本文書に記載された特定の目的を超えて以外使用することを同意します。深セン市倍思科技有限公司(当社デジタルエネルギー充電と放電)が本文書の最終的な解釈権を保有します。内容は、あらかじめ予告なく変更される場合があります。

Shenzhen Baseus Technology Co. Ltd. (Baseus Digital Portable Power Station) accepts no liability for damage, injury or any legal responsibility incurred directly or indirectly from the use of this product. Users shall observe safe operation guidelines including, but not limited to, those set forth herein.

深セン市倍思科技有限公司(当社デジタルエネルギー充電と放電)は、本製品の直接または間接的な使用によって生じた損害、負傷、または法的責任について責任を負わないものとします。お客様は、本取扱説明書に記載されているものを含むがこれに限定されない、すべての安全ガイドラインに従う必要があります。

EN

1. Function Description

* This product is developed based on industry-leading digital power technology. It supports PD3.1 140W fast charging, fully meeting your charging needs.
* This product uses a LCD screen to display real-time operation status (battery level, operating temperature, current input/output power, remaining charging time), charge and discharge reminder, port status, etc.
* This product has a total of 6 output ports, including 3 AC ports (rated output power: 420W, surge power of lower than 420W, such as non-mounted mini fridges, car-mounted mini machines, desk lamps, small hot cookers, etc.).
* It supports simultaneous power output of up to 6 products, with a maximum of 140W PD fast charging via a single Type-C port. It also supports simultaneous multiple protection for USB (Type-C) lowest fast power output to meet the charging needs of digital products.
* Supports no more than 2 methods of input for charging: Type-C/ PD3.1 fast charging (140W Max.), DC port charging (500W Max.).
* This product supports wireless charging of Qi2 25W protocol, supporting direct power supply via car-mounted chargers and direct charging via some panels with MCA interface.
* The built-in LED lighting provides three lighting modes: long light, SOS, and strobe. You can switch the mode by pressing the button or adjust the brightness of the long light via the app.

2. Product Specification

Name：Digital Power 4μs/s 420W
Model No.: BPE45B
Input:Type-C:5V⎓3A/9V⎓3A/15V⎓3A/20V⎓5A(MAX)=280WIN
Solar DC Input: 11-29V⎓8A 100W Max.
Type-C1 Input: 5V⎓3A/9V⎓3A, 12V⎓3A, 15V⎓3A, 20V⎓5A 140W Max.
AC Output: 100V-120V⎓3.5A Max 420W (Pure Sine Wave, Pure Power 480W)
USB1/USB2 Output: 5V⎓3A, 9V⎓3A, 12V⎓2A, 12V⎓1.5A
Type-C1/Type-C2 Output: 5V⎓3A, 9V⎓3A, 12V⎓3A, 15V⎓3A, 20V⎓5A 140W Max.
Type-C2 Output: 5V⎓3A, 9V⎓3A, 12V⎓2.5A
Type-C1+Type-C2 Output: 100W-30W
USB1+USB2 Output: 5V⎓3A
USB1+Type-C1&C2 : 30W+30W
USB2+Type-C1&C2 : 5V⎓3A
Type-C1+Type-C2+USB1+USB2&LTC : 100W+25W
DC+車載充電器出力：11.5V⎓7A 100W Max.
Wireless Output: 25W
製品サイズ：260×170×128mm
本体重量：約 5.1kg
取付金具：なし(US/JP)
付属品：電源コード*1、ソーラー充電ケーブル（MC4⇔DC5.5/2.1）、車載シガー/汽車充電ケーブル Type-C to Type-C（240W）、取扱説明書、保証書

3. Package Including

Baseus IoTa Series Portable Power Station 420W(US/JP 110V) ×1
Solar Charger Cable (MC4 to DC Input) ×1
Car Charger Cable + Charging Data Cable Type-C to Type-C (240W) ×1
User Manual ×1
Warranty Card ×1

4. Schematic Display of Product



Download the Baseus App and User Manual

Scan the QR code on the right for the download address with your mobile device, or http://app.baseus.com (download in other languages) in the search bar to download the app.
Open the Baseus app and register/ log in. If you have registered, please login directly), login, add equipment, and then connect and operate.



5. Instructions

Note: The following instructions assume that the APP has been connected to the product. If the connection is broken or the distance between them is too far (over 10 meters), the APP may not be able to instantly respond or issue reminders. Please keep the APP and the product close for user convenience. It is recommended to use the product while keeping the APP on and keep them close for smoother use.

1. Start/Shutdown

* Press the power button for 1s to turn on the product, the power indicator lights up, screen prompts to enter standby mode
* In the power-on state, press and hold the power button for 2 seconds to turn it off with the power indicator off.



* The default standby time of this product is 10 minutes. If the inverter switch/USB light switch is off and the product has no load accessed, the product will automatically turn off in 10 minutes.

2. How to charge a device

1) Charge a device via a USB Type-C/DC port

* Turn on the product, connect the USB Type-C/DC port will enter the standby mode and can be used to charge cell phones or other digital products with compatible data cables.
* Meanwhile, the main screen will display all parameters for reference, including the current total output power, current temperature, remaining battery level, and remaining discharge time under the current output power.



2) Charge a device via the AC port

* After the product is turned on, press and hold the AC output button for 2 seconds to enable AC inversion output, with the AC output indicator on. Now you can plug in and charge an AC device.
* After the product is turned on, press and hold the AC output button for 2 seconds to disable AC inversion output, with the AC output indicator off.

⚠ **Warning: There is a high-voltage output after the AC inversion output is enabled. Please do not plug metal or conductive objects into the AC main socket to avoid electric shock!**

3. How to charge the product

This product supports up to 140W PD fast charging, and accommodates all adapters and car-mounted chargers that are compatible with the PD protocol.



DC charging

* The DC port supports the APPT protocol, and can be charged with car-mounted chargers or solar panels.
* The DC port is powered off by default. Press the power on-state automatically in order to monitor all modules and provide feedback on operation status in real time



Note:

* **The product will not enter automatic shutdown when it is charged with a device through USB Type-C/DC/AC ports.**
* **The value of each parameter on the main screen is measured by a built-in program, which may be subject to errors and changes in real time. The parameter information is for reference only.**
* **The time for the charging and discharging of this port in the APP for more details about the charging and discharging of this port.**

4. LED Lighting

* This product come with a LED flood light for emergency lighting needs.
* Press and hold the LED switch/mode switch button for 2 seconds to turn on the LED light. The light has a default state of staying on for 10 minutes. Press the button to switch between different modes, which are SOS and strobe.
* Press the button to adjust the brightness under the long-on mode in the app.
* Under the LED lighting state, press and hold the LED switch/mode switch button for 2 seconds to turn off.

Note: If the LED lighting is on, the default standby time of this product will be adjusted to 5 hours for any need of emergency lighting at night.



5) Advanced use of the APP

1) You can contact Baseus for 1on 1 customer service via the app to solve problems you may have.

2) The device name can be edited in the app.

6) FAQ

1) What type of battery is used in the product?
This product uses high-quality automotive-grade lithium iron phosphate battery.

2) What equipment can be charged via the AC output port of the product?
The AC output of the product is rated at 420W with a peak power of 840W, being able to supply power to most consumer electronics and household appliances. Please check the power of the equipment and make sure that the total power of all load equipment is lower than the rated power before using it.

3) How do I know how long the product can supply power?
The LCD display will show the remaining battery life and calculate a remaining discharge time based on the current power, which is for reference only.

4) How can I tell the product is charging?
When charging, the LCD display will show the remaining charging time and input power.

5) Does the product support simultaneous charging and discharging?
The Type-C port and USB port support simultaneous charging and discharging; when using the DC port to charge the product, it does not support output charging.

6) Can I use the product in the rain?
Please use a dry, soft and clean cloth or paper towel to wipe this product.

7) Can I carry this product on the plane?
Equipment no larger than 100Wh is allowed on planes. This product is 2688Wh, so it is not allowed on planes.

8) How do I store and maintain the product?
* It is recommended to use or store the product with a temperature of 20-30°C, and keep it away from water, heat source and metal objects.
* For long-term storage, please charge and discharge the product once every 3 months (discharge it to 30% and then charge it to 50%).

* **For safety reasons, do not store this product when the temperature is higher than 45°C or lower than -20°C for a long time.**
* **If the product has been stored for a long time and cannot be charged or discharged, please charge it for a short time in a few full batteries, its battery core will suffer irreversible damage and the service life of the product will shorten.**
* **If the product has low remaining power and has been idle for too long (not in over-discharge state), it will enter deep sleep mode and need to be charged before being used again.**

6. Common Problems & Troubleshooting

Details of Error Icons	Error Type	Recovery Methods
Icon flashes	USB overload protection	Remove the abnormal load and normal operation will resume automatically once the load is normal.
Icon flashes	Type-C overload protection	Remove the abnormal load and normal operation will resume automatically once the load is normal.
Icon flashes	Type-C high-temperature protection	Normal operation will resume automatically after the battery cools down.
Icon flashes	Battery charging high temperature protection	Normal operation will resume automatically after ou stop the charging and place it in a cool and ventilated place.
Icon flashes	Battery discharge high temperature protection	Normal operation will resume automatically after the battery cools down.
Icon flashes	Battery charging low temperature protection	Normal operation will resume automatically after the battery temperature is restored to above 5°C (41°F).
Icon flashes	Charging overload protection	Normal operation will resume automatically after the abnormal load is removed.
Icon flashes	AC output overload protection	Normal operation will resume after removing the over-powered device and reserving the product. Electrical appliance must be powered on simultaneously.
Icon flashes	AC over-temperature protection	Please remove the abnormal load, and put the product in a cool and ventilated place, and it will resume normal automatically.
Icon flashes	Low-temperature protection	Normal operation will resume automatically after the temperature is restored to above 0°C (32°F).
Icon flashes	Fan blocking	Please check whether the fan is blocked by foreign objects and remove them if so.
Icon flashes	DC overload protection	Normal operation will resume automatically once the load is normal.
Icon flashes	DC high temperature protection	Normal operation will resume automatically after the product cools down.
Icon flashes	Battery discharge low temperature protection	Normal operation will resume automatically after the battery temperature is restored to above 5°C (41°F).
Icon flashes	Battery discharge undervoltage protection	Please charge the product immediately.
Icon flashes	Failure of communication with BMS	Normal operation will resume automatically after being restarted.

If any alert occurs during the use of this product and the alert icon does not disappear after the product is restarted, please stop using the product immediately (do not attempt to charge or discharge). If the above information fails to resolve your problem, please contact customer service for further support.

JP

一、製品規格について

* 本製品は業界の最新のデジタル電源技術の研究開発に基づき、PD3.1 140Wを搭載し対応、
* 本製品はLCDスクリーンを採用し、リアルタイムの運転状態（バッテリー残量、動作温度、現在の入力/出力電力、残りの充電時間）、充放電のリマインダー、ポートステータスなどを表示できます。
* 本製品は合計6つの出力ポートを備えており、3つのACポート（定格出力：420W、瞬間最大出力420W未満（例えば、非搭載ミニ冷蔵庫、車載ミニ機械、電気スタンド、小型炊飯ジャーなど）に電気を供給することができます。
* 最大6つの製品を同時に給電および充電でき、1つのType-Cポートから最大140Wの快速充電を対応し、USB（Type-C）ポートをデジタル製品の充電ニーズを満たすために、デジタル製品の最低電力出力を対応しています。
* Type-C/PD3.1充電使用（140W Max.）、DCポート充電（500W Max.）の最大2種類の入力充電に対応。
* 本製品はQi2 25Wワイヤレス充電プロトコルを内蔵しており、車載充電器と特定のMCAインターフェースのソーラーパネルから直接電力を対応します。
* スタンドライトは3段階、ロングライト/SOS/ストロボの3つの照明モードを備えており、ボタンでライトを切り替えるか、APPでロングライトの輝度を調整することもできます。

二、製品仕様

製品名：デジタルパワーパン 4μs/s
型番：BPE45B
入力：Type-C：5V⎓3A/9V⎓3A/15V⎓3A/20V⎓5A(MAX)=280WIN
ソーラー入力：11-29V⎓8A 100W Max.
Type-C入力：5V⎓3A/9V⎓3A/12V⎓3A, 15V⎓3A, 20V⎓5A 140W Max.
AC出力：100V-120V⎓3.5A Max 420W（正弦波、ピーク電力480W）
USB1/USB2出力：5V⎓3A/9V⎓3A/12V⎓2A/12V⎓1.5A
Type-C1/Type-C2出力：5V⎓3A/9V⎓3A/12V⎓3A/15V⎓3A/20V⎓5A 140W Max.
Type-C2出力：5V⎓3A/9V⎓3A/12V⎓2.5A
Type-C1+Type-C2出力：100W-30W
USB1+USB2出力：5V⎓3A
USB1+Type-C1&C2：30W+30W
USB2+Type-C1&C2：5V⎓3A
Type-C1+Type-C2+USB1+USB2&LTC：100W+25W
DC+車載充電器出力：11.5V⎓7A 100W Max.
無線出力：25W
製品サイズ：260×170×128mm
本体重量：約 5.1kg
取付金具：なし(US/JP)
付属品：電源コード*1、ソーラー充電ケーブル（MC4⇔DC5.5/2.1）、車載シガー/汽車充電ケーブル Type-C to Type-C（240W）、取扱説明書、保証書

三、包装内容明細

優塔（IoTa）エネルギーステーション携帯ポータブル電源420W（110V US/JP）×1
ソーラー充電ケーブル（MC4⇔DC5.5/2.1）×1
車載シガー汽車充電ケーブル Type-C to Type-C（240W）×1
取扱説明書×1
保証カード×1

四、製品機能について（詳細ビデオチュートリアルの説明）

Baseus APPおよびユーザーガイドのダウンロード

モバイルデバイスの右側を、携帯ミニの検索バーにスキャンしてダウンロードアドレス、またはhttp://app.baseus.com（他の言語）をダウンロードします。
APPをダウンロードしてください。
登録/ログインを行ってください。
APPをダウンロードしてください。

五、製品の使用

ご注意：充放電機能時では、ダウンロードAPPおよびご製品と相互接続されています。接続が切れる、距離が遠いほどメーカーは上限、APPおよびご注意下さるため、距離またはメーカーまたはプログラムで表示できない場合があり、製品および使いやすいように、APPと製品を近くに置いてください。より良い製品体験を得るようにお勧めします。

1. 電源のオンとオフ

* 電源ボタンを1秒長押しすると電源を点灯させることで、電源ボタンのインジケーターが点灯し、画面が待機モードに入ります。
* 電源ボタンを2秒間長押しすると、APP画面、続けると、製品の電源がオフになり、電源ボタンのランプもオフになります。



* 本製品のアイドルのスタンバイ時間は10分です。インバータスイッチ/USBライトスイッチがオンになっており、製品が出力の負荷にも接続されていない場合、製品は10分後に自動的にシャットダウンします。

2. 充外電充方法

1) USB-Type-C外充電

* 製品の電源をオンにし、USB-Type-C/DCポートがスタンバイ状態になり、対応するデータケーブルをインターフェイスに接続したら、携帯電話やその他のデジタル製品を充電することができます。
* その間に、画面には、現在の充電合計出力電力、残量温度、現在電力、および出力電力時間などの各パラメータ情報が表示されます。



2) AC外部充電

* 電源ボタンを2秒以上押し続けると、ACスクリーンオンになり、ACスクリーンがオンになり、ACランプが点灯します。ACデバイスを充電できます。
* ACランプが消えるまで電源ボタンを2秒以上押し続けると、ACインバーターがオフになり、同時にACランプが消灯します。

⚠ **警告：インバーターのACが出力されるごとがあるため、危険な高電圧出力が発生し、感電するため、ACソケットの挿入に金属やその他の導電性物体を挿入しないでください。**

三、充電方法

本製品は、最大140WのPD急速充電をサポートし、付属のユニバーサルPD対応充電器アダプター、自動車充電器、およびその他の機種を使用して製品を充電できます。

DC充電

* 本製品のDCポートは、APPプロトコルに対応しており、本製品の充電ポートの自動車充電器またはソーラーパネルから直接充電することができます。
* 本製品の電源をオンにすると、デフォルトで電源オンが閉じます。本製品の電力システムへの関連するシステムインターフェースをより適切に監視およびメンテナンスするために開始です。

ご注意：

* **1)USB-Type-C/DC/ACなど充電ポートインターフェース3つが同時使うた、充電の充電インターフェースが製品を充電している場合、製品は自動インバーターがオンになります。**
* **メインの画面のパラメータ：プログラムは、製品の組み合わせによって測定された値であり、特別なエラーが表示、リアルタイムで変更されている場合があります。このパラメータ情報は参考のみに、実際の状態に従ってください。**
* **各ポートの充電/放電時間：APPで各ポートの充電/放電時間をクリアを表示してください。**

4)LED照明

* 製品には緊急LEDが内蔵し、非常照明機能が提供できます。
* LEDスイッチ/モードボタンを2秒間長押しすると、LEDが点灯します。初期状態はロングライトが点灯、ボタンでSOS、ストロボなどの3つの異なるモードに変更することができます。
* APPでロングライトの輝度を調整することができます。
* LEDライトが点灯時に長押しLEDスイッチ/モードボタンを長押しすると、LEDライトが消灯します。

ご注意：LED照明がオンになっている場合、本製品のデフォルトの待機時間は、夜間の緊急照明のために5時間に調整されます。



5) APPのスクリプト使用

1) APPやカスタマーサービスを使用サービスについて一つを問い合わせて、お客様の問題を解決いたします。

2) APPで製品のデバイス名を変更することができます。

6) よくある質問

1) 製品はどのタイプのバッテリーを使用していますか？
本製品は、高品質の自動車用リン酸鉄リチウムバッテリーを使用しています。

2) 製品のAC出力ポートにはどのようなデバイスを充電できますか？
本製品のAC出力ポートの定格電力は420W、ピーク電力は840Wで、ほとんどの家電製品や電気小型機器を供給できます。使用前に電気製品の電力をチェックし、すべての負荷デバイスの合計電力が定格電力より小さいことを確認してください。

3) どのように製品がどのくらい電力を供給できるかを知っていますか？
本製品の液晶スクリーンは残存電力を表示し、この数値に基づいて残存電力を表示して、この時点の参考用のみです。

4) 製品が充電されているかどうかを確認するにはどうすればよいですか？
充電中、液晶スクリーンは充電残り時間と入力電力を表示します。

5) USBポート製品と充電ポートの同時充電をサポートしていますか？
本製品のType-CとUSBインターフェースは同時充電と放電をサポートしますが、DCポートを使用して製品を充電する場合、外部充電には対応しません。

6) 本製品をレインで使用できますか？
本製品は、乾いた柔らかい清潔な布またはペーパータオルでふいてください。

7) 本製品を飛行機に持ち込むことはできますか？
飛行機には100Wh以下の機器を持ち込むことができます。本製品は2688Whであるため、飛行機に搭載することはできません。

8) 製品の保管、維持、およびメンテナンス方法方法は？
* 本製品は、高、低、その他の温度帯から最も近い20～30℃の環境で使用または保管することをお勧めします。
* 長期保管の場合は、3ヶ月に1回の充電と放電を行うことをお勧めします（放電は30%まで充電、充電は50%まで充電）。

* **安全上の理由でうるため、本製品を45℃以上または-20℃以下の環境で長期保管しないでください。**
* **本製品の長期保存後で充電や放電が使用できない場合は、充電する前に数分間、バッテリーに接続して充電してください。そうしないとバッテリーを長期間アイドル状態にすると、バッテリーに不可逆的な損傷を与え、製品の寿命が短くなります。**
* **本製品の電力が低く長く、アイドル状態が保管する（過放電状態ではない）場合、製品はディープスリープモードに入り、製品を再使用する前に充電する必要があります。**

4. 画像の表示と処理

異常アイコンの説明	対応タイプ	異常の回復方法
アイコンが点滅	USB過負荷保護	異常負荷を取り外し、正常になった後自動回復します
アイコンが点滅	Type-C過負荷保護	異常負荷を取り外し、正常になった後自動回復します
アイコンが点滅	Type-C高温保護	製品が冷却後に、自動回復します
アイコンが点滅	バッテリ充電時の高温保護	冷却後に、自動回復します
アイコンが点滅	バッテリ充電時の高温保護	バッテリ温度が下がると自動回復します
アイコンが点滅	バッテリ充電時の低温保護	バッテリ温度が下がると自動回復します
アイコンが点滅	充電過負荷保護	異常負荷の自動回復
アイコンが点滅	AC過負荷保護	「オーバーパワーデバイスを取り外し、家電を再起動すべき回復 製品を保存します。家電を同時に電源をオンにする必要があります。
アイコンが点滅	AC高温保護	異常負荷を取り外し、冷却の換気環境に置いた後に自動回復します
アイコンが点滅	DC過負荷保護	負荷が正常になった後、自動回復します
アイコンが点滅	DC高温保護	製品が冷却後に自動回復します
アイコンが点滅	バッテリ放電低温保護	バッテリ温度が下がると自動回復します
アイコンが点滅	ブザー故障不足電圧保護	できるだけ早く充電してください
アイコンが点滅	BMSの通信に失敗しました	再起動後に自動回復します

本製品の使用中に警報メッセージが表示され、再起動後も警告アイコンが消えない場合は、すぐに使用を中止してください！
作業中断にならないでください。

Statement on Toxic and Hazardous Substances in Electronic Information Products：

Part Name	Toxic or hazardous substances and elements					
	Lead (Pb)	Mercury (Hg)	Cadmium (Cd)	Hexavalent Chromium (Cr(VI))	Polybrominated Biphenyls (PBB)	Polybrominated Diphenyl Ethers (PBDE)
PCB	X	O	O	O	O	O
Metal	X	O	O	O	O	O
Plastic	X	O	O	O	O	O
Accessory	X	O	O	O	O	O

This form is prepared in accordance with SJ/T 11364 regulations.
O: Indicates that the content of the toxic and hazardous substances in all homogeneous materials are below the limit requirements specified by GB/T 26572 standard.
X: Indicates that contents of the toxic and hazardous substances exceed the limit requirements specified by GB/T 26572 standard, and are used in compliance with exemptions allowed in EU RoHS.
This product complies with EU RoHS 2 Directive (2011/65/EU).
The 5-year icon refers to the "effective life of environmental protection", i.e.the product quality assurance period. Within the specified period of time, the product will not leak or mutate, which will not cause serious environmental pollution, personal injury or property damage due to leakage, mutation or sudden crisis of toxic and harmful substances in the product, so that people can use the product with confidence. The "environmental protection use" means that all electronic products will be required to be recycled after the end of their service life, and will no longer be responsible for the quality of the products due to the safety risks that arise after the safe use period.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.
Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.
NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.
If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.

Warning:
Operation of this equipment in a residential environment could cause radio interference.

FCC ID:2AWCJ-BPE45B

警告：这不是电池充电器！请勿充电。
警告：请勿将电池放入火源，将电池存储在儿童接触不到的地方。

Warning: Please follow the steps carefully instructions! Please keep the battery away from children and fire.

Manufacturer: Shenzhen Baseus Technology Co., Ltd.
Add: 2nd Floor, Building B, Baseus Intelligence Park, No.2008, Aurgang Rd,
Gangtou Community, Bantian Street, Longgang District, Shenzhen
Industrial Standard: Q/BSSZ 0147
Hotline: 400-0000-139 Email: Website: www.baseus.com

倍思设计Designed by Baseus
中国制造Made in China

PB3813Z-P0A0
XXXXXXXX