

材质:200g哑粉纸 正反印刷
尺寸：100x138mm

Important Safety Notice

- 1. Do not mix up HDMI to RJ45 transmitter and RJ45 to HDMI receiver before installation.
- 2. Do not hot plug when it is working.
- 3. Use DC5V-12V power supply only. Make sure specification matched if using 3rd party adapters.
- 4. Static electricity will cause damage of the device, please do ESD protection when using the device.

Introduction

This HDMI Extender includes a transmitter unit and a receiver unit, allows HDMI signal to be transmitted up to 70 meters at 4K resolution using a CAT6/6A/7 network cable. It is perfect for outdoor advertising, video clips, monitor system, home entertainment, and conference, etc.


Features

- 1. Zero latency.
- 2. 4K@60Hz HDMI signal can be transmitted 70 meters through a CAT6/6A/7 network cable.
- 3. The receiver can extract the digital audio from the transmitter through the S/PDIF port, support ARC function.
- 4. Supports Dolby audio(Dolby Digital Plus/Dolby TrueHD/Dolby Digital)
- 5. Supports HDR(YUV4:4:4), EDID passback.
- 6. Transmitter support one HDMI loop-out.
- 7. Support KVM function.
- 8. One receiver can be powered by the transmitter via network cable, Only on the first receiver.
- 9. Anti-lightning, anti-surge, anti-static protection.

Disclaimer
The product name and brand name may be registered trademark of related manufactures. ™ and ® may be omitted on the user manual. The pictures in this user manual are just for reference. The terms HDMI, HDMI High-Definition Multimedia Interface, and the HDMI Logo are trademarks or registered trademarks of HDMI Licensing Administrator, Inc. We reserve the rights to make changes without further notice to a product system described herein to improve reliability, function or design.



Package Contents



Installation Requirements

- 1. HDMI source device (compute graphics card, DVD, PS3,)HD monitoring equipment etc.
- 2. HDMI display device like SDTV, HDTV, projector with HDMI port.
- 3. UTP/STP CAT6/CAT6A/CAT7 cable. Follow standard IEEE-568B, It is recommended to select a network cable with less loss and crosstalk.


2. Connection instruction

- 1) Connect the source device to the HDMI in port of the transmitter with an HDMI cable, and connect the HDMI out port of the receiver to the display device with another HDMI cable.
- 2) Connect the CAT out port of the transmitter and the CAT in port of the receiver via a network cable (CAT6/CAT6A/CAT7). If cascading is used, connect the CAT out port of the previous receiver to the CAT in port of the next receiver.
- 3) If using HDMI loop out, connect the display device to the HDMI OUT port of the transmitter.
- 4) Plug the power supply into the device to get started.

[NOTE]: It is recommended to use a length range within 2~70m network cable. If the cable is too short, there may be no display output because the signal is too strong. If the cable is too long, the output may be with poor quality.

Interfaces

1. Transmitter (TX)



①	USB Light	LED indicator keeps on and Fast flashing means the computer/PC have established or connected, slow flashing means no established connection
②	Reset button	Press to restart the device
③	RJ45 signal output	Connect with network cable
④	Power/Signal indicator	When there is power and no HDMI signal, the indicator will flash, when there is HDMI signal, the indicator will light solid blue
⑤	DC5V-12V input	Connect with DC5V-12V power adapter
⑥	HDMI output	Connect with HDMI display device
⑦	HDMI input	Connect with the source device
⑧	USB-A port	Connect with computer


FAQ

- Q: There is no output on screen when all connections are correct?
- A: 1) Please make sure the HDMI cables supports 4K×2K if the output signal from the source device is 4K×2K resolution.
- 2) Please check and make sure the network cable insert to the RJ45 port well.
- 3) Restart the transmitter or receiver by pressing the reset button.

- Q: Black screen happened on the display/monitor?
- A: 1) Check if the length of the cable is within the specified range.
- 2) Reset the transmitter to re-built the connection.

- Q: The display shows unusual color or no sound?
- A: 1) Reset the transmitter or receiver to re-built the connection.
- 2) Check if the HDMI cables are connected well.
- 3) Reconnect the network cable.

2. Receiver (RX)



①	USB Light	LED indicator keeps on and Fast flashing means the computer/PC have established or connected, slow flashing means no established connection
②	Reset button	Press to restart the device
③	Audio switch	Choose to decode audio from HDMI or ARC output from fiber optic interface
④	RJ45 signal input	Connect with network cable
⑤	Power/Signal indicator	When there is power and no HDMI signal, the indicator will flash, when there is HDMI signal, the indicator will light solid blue
⑥	DC5V-12V input	Connect with DC5V-12V power adapter
⑦	S/PDIF out	Output digital audio signal
⑧	HDMI output	Connect with HDMI display device
⑨	USB-A port	Connect with keyboard and mouse


Specification

	Items	Specification
Power Supply	Voltage/Current	DC5V-12V
	Power consumption	TX < 4W RX < 4W
HDMI Performance And Interface	HDMI compliance	HDMI 2.0
	HDCP compliance	HDCP 2.2
HDMI Performance And Interface	HDMI resolution	480i@60Hz, 480p@60Hz, 576i@50Hz, 576p@50Hz, 720p@50/60Hz, 1080i@50/60Hz, 1080p@50/60Hz, 3840x2160@24/25/30/60Hz 4096x2160@24/25/30Hz
	Supports audio formats	LPCM/DTS-HD/DTS-Audio/Dolby Digital Plus Dolby TrueHD/Dolby Digital
HDMI Performance And Interface	Input and output TMDS signal	0.7~1.2Vp-p(TMDS)
	Input and output DDC signal	5Vp-p(TTL)
	Input cable length	≤8m(AWG24)
	Output cable length	≤8m(AWG24)
Transmission Distance	CAT6/6A/7	≤70m
Protection Level	Electrostatic protection of the whole machine	1a Contact discharge level 3 1b Air discharge level 3 Implementation of the standard: IEC61000-4-2
Operating Environment	Working temperature	-20~60°C
	Storage temperature	-30~70°C
	Humidity (no condensation)	0~90%RH
Body Properties	Dimension	150.0(L) x 107.0(W) x 28.4(H)mm
	Material	Aluminium alloy material + crystal panel
	Treatment process	Grit blast
	Color	Black
Body Properties	Weight	TX: 260g RX:260g

Installation Procedures

1. Connection

one to one:



Note: Only the TX needs to be powered when one to one connection.

Follow the standard of IEEE-568B, It is recommended to select a network cable with less loss and crosstalk.

- 1-Orange/white 2-Orange 3-Green/white
- 4-Blue 5-Blue/white 6-Green
- 7-Brown/white 8-Brown



User Manual

HDMI EXTENDER

Point to Point Extender

