


VM17 / VM17L - 17 WAY DISTRIBUTION BOARD



SAFETY

This product complies in full with AS/NZS 61439.3.

This product should be installed by a suitably qualified person in accordance with Australian and New Zealand wiring rules.

INSTALLATION PROCEDURE

This product is designed to be installed inside a wall cavity only (flush mounting). Do not surface mount.

For surface mounting use VM17SK surface mount enclosure in conjunction with this board.

The metal wall enclosure must be earthed. Fold out tags (x4) on the side walls of the enclosure can be folded out to set the correct height onto the studs.

Door hinge pins are easily removable and the door can be reversed so that it swings either left or right. This product is designed to be used with New Zealand and Australia's MEN system.

DO NOT install a link between the neutral bars and earth bar on circuits dedicated to RCDs. Please ensure circuits and protective devices are adequately identified during installation.

SPECIFICATIONS

Rated Operational Voltage	415V AC maximum, 50Hz
Maximum Current	100A
Rated Insulation Voltage	1000V
Short Circuit Withstand	10kA

DIMENSIONS

Cover Assembly	323 x 402 x 35mm
Base (cut out size)	277 x 355 x 93mm

WARRANTY

This product is covered by a 1 Year Vynco Warranty - proof of purchase is required. Please contact Vynco for details of returns procedure.

NOTE: This product contains NO user serviceable parts.

VYNCO INDUSTRIES (NZ) LIMITED

CHRISTCHURCH

388 Tuam Street, Phillipstown, Christchurch, 8011
PO Box 9022, Tower Junction, Christchurch 8149
New Zealand
P +64 3 379 9283 F +64 3 379 6838
E sales@vynco.co.nz

VYNCO.CO.NZ

AUCKLAND



9 Levene Place, Mount Wellington
PO Box 12 249, Penrose, Auckland 1061
New Zealand
P +64 9 525 6051 F +64 9 525 5799



VM17 / VM17L - 17 WAY DISTRIBUTION BOARD

EARTH AND NEUTRAL BUSBAR LAYOUT

	Material	Number of Bars	Double Screw Tunnels	Single Screw Tunnels
Earth Bar	Brass steel	1	3	12
Neutral Bar	Brass steel	1	2	8
RCD Neutral Bar	Brass steel	3	1	3



REMOVING DOOR

STEP 1



Rotate top pin 90°.

STEP 2

Slide pin down to release door. There is no need to remove pin completely.

STEP 3

Lift and remove door.



FITTING DIAGRAM

To fit into wall cavity, fold out tabs to set height of enclosure onto studs.