



Instruction
Manual

CYAN AXIS
MIXED LIGHT



BT5.0/ 2.4G/usb
THREE-MODE



L800 (BLUETOOTH, 2.4G, WIRED) THREE-MODE
61 KEY MECHANICAL KEYBOARD

Three-mode connection instructions: //////////////////////////////////////

Bluetooth link:

Long press **FN+Z=BT1** to connect to the first device, long press FN+Z button for 3 seconds, the blue light of Z button flashes quickly, Bluetooth is in pairing state, and the paired one, tap FN+Z again to return Connect the device.

Long press **FN+X=BT2** to connect to the second device, press and hold the FN+X button for 3 seconds, the blue light flashes quickly, the Bluetooth is in the pairing state, and the paired one, tap FN+X again to return Connect the device.

Long press **FN+C=BT3** to connect to the third device, long press FN+C for 3 seconds, the blue light flashes quickly, the Bluetooth is in the pairing state, and the paired is already paired, tap FN+C again to return Connect the device.

Note: When the keyboard is in the current Bluetooth state, the switch is also a direct switch between FN+ZXC to link the Bluetooth device..

2.4G link:

Long press the **FN+B=2.4G key**, then the keyboard code matching light will flash blue light, the receiver is plugged into the computer's USB port, the connection success light will turn bright blue light.

Wired link:

Press the **FN+V=USB key**, the keyboard code matching light will flash white light, the keyboard code matching light will become long and bright white, the keyboard is connected with the computer TYPE-C line.

Compound function key switch:////////////////////////////////////

- FN + ← = Lighting effect switch

FN + [{ = Decrease the lightness

FN +] } = Increase the lightness

FN + ; : = Slower the light effect

FN + ' " = Faster the light effect

FN + WIN = Lock the key WIN and APP

FN+A= Play/Pause

FN+S= Precious track

FN+D= Next track

FN+F= Decrease the volume

FN+G= Increase the volume

FN+H= Mute
- FN+J= Insert

FN+K= Home

FN+L= Page Up

FN+U= PrtScr SysRq

FN+I= Scroll Lock

FN+P= Pause Break

FN+M= Delete

FN+<= End

FN+>= Page Down

FN+Esc=.

FN+Shift+Esc=~

FC CE RoHS Made in China

Product specifications: //////////////////////////////////////

Specification item	Three-mode mechanical keyboard
Product number:	L800
Interface Type:	TYPE-C
Connection method:	Bluetooth 5.0、 2.4G、 Type-C Wired
product type:	Mechanical keyboard
Built-in battery capacity:	2200mA
Number of keys:	61KEY
Button life:	50 million times or more
Operating Voltage:	5.0V±5% DC
Working current:	150mA (MAX)
Product Size:	(L) 289mm * (W)101mm x (H)38mm
Keyboard weight:	590g
Cable length:	1.75m
Keycap material:	ABS two-color injection
System compatibility:	Compatible with IBM PC Win98SE/Me/2000/XP/VISTA/WIN 7/WIN10
Supported devices:	Multiple devices such as mobile phones, tablets, and desktop computers can be connected at the same time.