




Installation Instructions



Powerpoint Double, Horizontal 10A, 220-240V a.c.

Product Code:
**KF2PPHB series/KE2PPHB series
H2PPHB series**

APP Installation

Visit www.kasta.com.au or your app store to download the free KASTA app.
iOS: requires iOS 9.0 or later.
Android: requires Android 4.4 or later.
Devices must support Bluetooth 4.0



Important Safety Information

- This product must be installed by a licensed electrician in accordance with all the requirements of AS/NZS 3000 (current edition) and other relevant Standards and Regulations.
- Electricity MUST be disconnected prior to installation. Failure to do so may result in serious injury and or loss of life.
- Indoor use only. Not suitable for damp or explosive environments.
- Complies to Australian Standards AS/NZS 60950.1:2015, AS/NZS CISPR 15.
- No user serviceable parts inside.

FEATURES

- Control and monitor appliances with a standard 2 or 3-pin plug.
- 2x 10A individually switched power outlets.
- Simple 3 wire connection – A, N, E.
- Pair with KASTA remote switch devices for control (up to 8x maximum).
- Smart functions per outlet programmed via phone/tablet with the KASTA app. This includes schedules, timers, scenes and groups.
- Child Lock function per outlet (lock outlet in off state) activated from the button or the KASTA app.
- Energy monitoring function per outlet viewed from the KASTA app.
- Built in overvoltage, overcurrent and overtemperature protection.

FUNCTION SETUP

Operate via individual Load Control Button.

ON/OFF BUTTON	1 CLICK
---------------	---------

Turns load on or off. Button LED indicator is white when on.

CHILD LOCK	4 SECOND LONG PRESS (WHEN OUTLET IS OFF)
------------	---

Button LED indicator changes to green if successful after long press (four seconds).
Long press (four seconds) again to deactivate.

DELAY TO OFF	3 CLICKS
--------------	----------

Load automatically turns off after set time selected via the app.
LED indicator will flash 3 times if successful. 1 click to cancel.
LED indicator will flash once.

FACTORY RESET	9 CLICKS
---------------	----------

Restores all settings back to factory.

*If successful, light and LED indicator light will pulse the number of times that the button was clicked, indicating function.

TECHNICAL SPECIFICATIONS

Operating Temp: -20°C to 40°C

Supply: 220-240V AC 50Hz

Maximum Load: 2 x 10A (2400W)

CONNECTION DIAGRAM

