

Selore

&S-Global

Instruction Manual

12 in 1 USB-C HUB to 2xHDMI+RJ45+2xUSB2.0+2xUSB3.0+SD/TF Card Reader+Audio+PD+USB-C

ENGLISH

Product Introduction

This is an alloy multi-function USB-C HUB adapter. It mainly extends the USB-C interface of the source device to HDMI, network RJ45 interface, USB3.0-A, Audio, SD/TF card reader and USB-C charging port.

Note:
The USB-C source devices (mobile/notebook/tablet PC) must support video output.

Structure Diagram

1

2

3

4

5

6

7

8

9

10

1. Audio/Mic

2. USB 3.0

3. USB 2.0

4. SD&TF

5. RJ45

6. **HDMI**2

7. **HDMI**1

8. USB2.0

9. USB-C Data

10. PD3.0

Features

1. 3.5mm Audio & Microphone

2. USB3.0: 5Gbps, 5V0.9A@4.5W

3. USB2.0: 480Mbps, 5V0.5A@2.5W

4. SD/TF Card Reader: SD & TF can work simultaneously

5. Max Ethernet Speed: 1000M

6. HDMI 2: 4Kx2K 30Hz / 3840x2160 max

7. HDMI 1:

4Kx2K 60Hz / 3840x2160 (work separately while source is DP1.4)

4Kx2K 30Hz / 3840x2160 (work separately while source is DP1.2)

8. USB2.0: 480Mbps, 5V0.5A@2.5W

9. USB-C: 5Gb/s data transfer,downward compatible with USB2.0, power supply up to 4.5W Max.

10. USB-C PD3.0: Upstream charging the source devices such as Laptop/Notebook, charging limited to 87-96W for safety and affected by different firmware. Support 100W power adapter Support SST/MST

Comply with USB-C interface specification

Built in conversion chip, plug and play

Connection

Mobile

Notebook

Tablet PC

USB-C

USB3.0

USB2.0

HDMI

AUDIO

SD/TF

MONITOR

ETHERNET

CARD READER

U FLASH DRIVE

KEYBOARD

MOUSE

Note :

1. For Video output, USB-C source devices must support video output.

2. Suggest charge for power supply to keep it work stable.

Display Settings for win10

Right click desktop >Display Settings

Home

Time & Settings

System

Display

Notifications&actions

Power & Sleep

Battery

Storage

Tablet Mode

About

Display

Select and rearrange displays.

Select a display below to change its settings.

Some settings are applied to all displays.

1

2

3

Resolution

1920x1080(60Hz, 3D)

1680x1050(3D)

1600x900(3D)

1440x900(3D)

1400x1050(3D)

1366x768(3D)

1366x768(30)

1280x1024(30)

1280x960(30)

3D显示模式

开

Graphics Settings for win10

Right click desktop >Graphics Settings >Display

General Settings

Color Settings

Multiple Settings

Custom Resolutions

DisplayPort Topology

Select Display Mode

Single Display

Clone Display

Extended Desktop

Collage

Select One or More Active Displays

Built-in Display

HDMI Display

HDMI Display

Sound Settings for win10

Select Playback device

Speaker/Headset

Digital Display Audio 1

Digital Display Audio 2

50

1.Clone mode

Right click desktop >Graphics Settings >Display

General Settings

Color Settings

Multiple Settings

Custom Resolutions

DisplayPort Topology

Select Display Mode

Single Display

Clone Display

Extended Desktop

Collage

Select One or More Active Displays

Built-in Display

HDMI Display

HDMI Display

Source device

HDMI Display

HDMI Display

2.Extended Desktop

Right click desktop >Graphics Settings >Display

General Settings

Color Settings

Multiple Settings

Custom Resolutions

DisplayPort Topology

Select Display Mode

Single Display

Clone Display

Extended Desktop

Collage

Select One or More Active Displays

Built-in Display

HDMI Display

HDMI Display

Source device

HDMI Display

HDMI Display

HDMI Display

HDMI Display

Resolution Setting for Mac

Apple logo>System Preferences>Displays

Display

Color

Optimize for: Digital Display

Best for Digital Display

Scaled

1920x1080

1680x1050

1600x900

1440x900

1400x1050

1366x768

Show low resolution modes

Brightness: Automatically adjust brightness

Gather Windows

Sound Setting for Mac

Apple logo>System Preferences>Sound

Sound Effects

Output

Input

Select a device for sound output:

Name

Type

Internal Speaker

Built-in

Digital Display

DisplayPort

Settings for the selected device:

The selected device has no output controls

Output Volume

Mute

Graphics Settings for Mac

1.Mirror Display

Apple logo>System Preferences >Displays

Display

Arrangement

Color

Night Shift

To rearrange the displays, drag them to the desired position.

To relocate the menu bar, drag it to a different display.

Mirror Displays

Airplay Displays: Off

Show mirroring options in the menu bar when available

Gather windows

Source device

HDMI Display

HDMI Display

2.Extend Display

Apple logo>System Preferences >Displays

Display

Arrangement

Color

Night Shift

To rearrange the displays, drag them to the desired position.

To relocate the menu bar, drag it to a different display.

Mirror Displays

Airplay Displays: Off

Show mirroring options in the menu bar when available

Gather windows

Source device

HDMI Display

HDMI Display

Storage Conditions

Ambient Operating Temperature: 0℃ to 70℃(32°F to 158°F)

Storage Temperature: -30℃ to 120℃ (-22°F to 248°F)

Ambient Operating Humidity: 20%-80%RH

Storage Humidity: 20%-90%RH

FAQ

A. Why there is no video output?

1. Pls make sure your USB-C source devices support video output

2. Pls check the connection is good

3. Pls use standard HDMI cable

B. Why there is no audio output from HDMI port?

1. Pls make sure that there is audio output function on the monitor.

2. Pls set the external monitor as default audio output device.

C. Sometimes WIFI stopped working while hard disk connected to hub, how to do?

R: 2.4G network is easily disturbed. You can switch to 5G network.

Or you can adjust the placement of the hard disk, move to suitable place.

D. Win10 system, if one of display does not display, how to do

R: Right click desktop > Graphics Settings > Select One or More Active Displays

E. If USB driver cannot be identified, how to do?

R: Restart the computer and reconnect the product

F. If speed is too slow when connect hard disk, how to do?

R1: Plug and pull out for more times

R2: Restart the computer and reconnect the hard disk

R3: If you used USB3.0 hard disk, please make sure connect to the USB3.0 port not USB2.0.

G. If display stopped after connect high current hard disk, how to do?

R: Must be charged. Please supply power by power adapter.

FC

CE

RE

RoHS

WEEE

HDMI

MADE IN CHINA