一、下载安装APP

1.扫描下方二维码点击安装或者打开手机App store/手机应用宝搜索UBox下载安装。

二、注册登录账号

1.打开APP点击注册账号，输入手机号或邮箱地址后并点击同意用户协议，点击注册按钮获取验证码。（为了更好的用户体验，请允许所有通知权限，避免通知获取不到）



2.输入验证码点击下一步。（如果是邮箱注册，没有找到验证码，可以查看垃圾邮箱是否收到。）



3.设置登录密码，（为了您的密码安全，密码要求是8位以上的英文字母与数字的组合）设置完成后点击注册按钮完成注册。



4.输入注册所用的手机号或邮箱地址 后再输入密码点击登录。



三、设备连接

1.点击“添加家庭或设备安装位置”根据提示输入家庭名称添加地址。



2.输入您的家庭名称后点击下一步。



3.输入国家或地区、省份等必填内容，点击完成。



4.点击添加智能设备。



5.给设备接通电源，请确保手机已经连接上可用的WiFi ,选择安装智能设备。



6.开始设置前确保设备在配置状态。设备接通电源后，进入配置状态，设备蓝色LED会闪烁。



7.如果蓝色LED没有闪烁，说明设备状态不正确，请按键唤醒设备，再按住复位键直到蓝色LED灯亮后放开，蓝色LED闪烁说明进入了配置状态。（以下图片仅供参考）



8.给设备起个名字，选择家安装设备地址，点击下一步，APP默认设备名称为智能摄像机，用户也可以自己修改。



9.APP会自动填入WIFI名称，请填写对应的WiFi密码。可选择二维码配置或者声波配置。



10.二维码配置：选择二维码配置，将手机屏幕放在设备镜头正前方10cm处，请保持摄像头正对着二维码，摄像头扫描到二维码后APP会自动完成设备配置。



11.设置完成，设备自动进入设备列表界面，恭喜您，设备已经完成安装了。



12.关于PIR人体侦测功能提示。

*设备设置中可以设定人体检测灵敏度。在人流较多的环境下使用，建议关闭或者将设备设为低灵敏度，以避免不必要的唤醒延长电池使用时间。

*关闭：此状态下，设备不会进行人体感应侦测.
*低：设备休眠状态下，连续7秒感应到人体触发报警。
*中：设备休眠状态下，连续5秒感应到人体触发报警。
*高：设备休眠状态下，连续1秒感应到人体触发报警。



四、设备使用说明



点击进入家庭或设备安装位置

推送开关，点击可关闭推送。

设置按钮，点击可分享权限、选择开通云服务、删除设备

点击进入预览界面

点击可添加智能设备

账户和增值业务管理



点击设置按钮进入设备设置、基本信息界面
可设置“存储管理、图像翻转、环境模式、PIR人体侦测、休眠时间、电源频率、LED指示灯、设备名称”
可查询“名称、ID、型号、固件版本、厂商、检查固件版本”等信息。

声音开关按钮

实时拍照按钮

TF”与“云存储”转换按钮

实时录像按钮

麦克风按钮



查看我的账户信息及修改密码；

查看云服务开通状态及开通云服务；

开通AI云存储添加人脸识别及查看人脸识别状态；

添加我的好友设置分享权限及查看好友列表；

通用设置声音及监控默认清晰度；

查看APP版本信息

点击右上角的日历图标，选择日期即可看到当前日期的所有云视频



选择你需要查看的日期就可查看当日的所有云视频



五、注意事项

1.本设备使电池供电，电池使用时间会受到设备唤醒时间和唤醒次数影响，所以人体感应报警侦测功能，在人流较多的环境下使用，建议关闭或者将设备设为低灵敏度，以减少设备唤醒和呼叫次数延长电池使用时间。
设备电量不足时请及时充电，长时间电池欠电可能会造成电池失效。

2.在安装过程中请确保安装环境下网络正常，特别是在室外/门外安装，需要检查WiFi是否覆盖，如果WiFi信号比较弱，需要选择中继套装或者增加WiFi中继改善信号。

3.本设备属于低功耗智能产品，可以支持APP远程唤醒，PIR人体侦测唤醒，按键唤醒,每次唤醒后工作短暂时间后自动进入休眠状态，设备的工作时间可以在APP菜单中设置。

4.因为中国大陆地区收不到Google的系统推送消息，需要在手机中打开APP的自启动功能才可以收到推送消息

5.本设备提供一个月的免费云存储和人脸识别服务，在试用期满后如果需要继续使用增值服务需要在APP中购买。

UBox

APP使用说明简易手册

APP随着版本更新，会有一些修改，说明书仅供参考

---

1. APP INSTALLATION

(1.) Scan the following QR codes or seach for ˋUBoxˊ from the App Store(for iOS devices) or Google Play Store (for Android smartphones) to download and install the app.

2. APP REGISTRATION

(1.) Open the app then input your E-mail address then press 'Register'.
Check and select to agree the agreement then your E-mail box will get an verification mail.
(For better user's experience, please allow to open all permissions to avoid missing any notifications from the app.)



(2.) Set the login password and confrim the login password.
Then press 'Register' to next step.
(For your password safety, the password requires more than 8 characters plus combination of letters)



(3.)We send a verify mail to you, go to your mail box click the link to complete the verification.



Congratulations! Your registration is completed.We sent a validation mail to fangwenvip@126.com, please click the link in email to complete validation.

(4.) Enter your E-mail address, and password , click login .
(APP will auto fill the account infomaion)



3. WI-FI CONNECTION

(1.) Press 'Add Family' then set the room or position as per reminders.


There is no family in your app, click the button below to add a family.
Add Family

(2.) Enter your family name and then press 'Next'.



(3.) Input the necessary information just like Country, Province, then press 'Done'.



(4.) Press 'Add a device' to add a smart device



(5.) Connect the device with power supply, and make sure your mobile phone is connected to an available Wi-Fi. Then press 'Setup device'.



(6.) After the power on the device, wait for the device bule LED are blinking Which means your device in pairing mode



(7.) If the device blue are not blinking, please press the power/Call key to wake up the device first, then hold and press the RESET button until the blue indicator to light up and then release. The device will reboot and enter the pairing state.



(8.) Set the device name and select the device loaction befroe setup ,



(9.) The app will input the Wi-Fi name automatically, please input the correct Wi-Fi Password. Then you can choose the 'QR code configuration' or 'Sound wave configuration' .



(10.) QR code configuration: Select the QR code configuration then the mobile phone display a QR code. Use the device to scan to the QR code 10cm away from the mobile phone.



(11.) The device will enter to the device list automatically.
Setup success! The device is ready to use.



(12.) Notes about PIR detection

*User can change the PIR detection sensitivity in device setings.we recommend to set sensitivity at "Disabled" or "Low" to reduce flase alret and save the battery power in noisy environments.

*Disabled: disabled PIR detection.
*Low: deleay 7 seconds PIR detects a moving.
*Medium: deleay 5 seconds PIR detects a moving.
*High: deleay 1 second PIR detects a moving.



4. USING THE APP



Enter to select your family or smart device location

Turn on/off the push notification.

Settings: Sharing, Cloud storage, Delete the device..

Press to enter the preview section.

Press to add a smart device

Account and value-added account management



Smart device basic settings
Could set ˋStorage management, Flip screen, Environmental model,PIR detection, Sleep time, Power frequency, LED indicator, Device nameˊ
Could check the information of ˋDevice name, Device ID, Model, FW version, Manufacurter, Check for the FW updates..ˊ

Turn on/off the speaker

Screenshot

Playback switch 'Micro SD memory' and 'Cloud storage'

Take a video for the live view

Microphone - Speak to the smart device side.



Check ˋmy accountˊ name and change password;

Check and purchase the Cloud storage;

Check and purchase the AI Cloud Facial Recognition;

Check and add my friends list and permission;

Set the default voice and resolution for the devices;

Check the App version.

Click the ˋCalendarˊ icon on the right top corner , then choose the date to playback the vicoes from cloud storage.



Choose the desired date to check all videos from the cloud.



5. SPECIAL NOTES!

(1.) The device is equipped with a rechargeable lithium battery. The battery life will be affected by the device wake-up time and the number of wake-ups.
Therefore, the PIR sensor alarm detection function is used in an environment with a lot of people.
It is recommended to turn off or set the device to low sensitivity to reduce device wake-up and call times extend battery life.
When the battery is low, please charge the battery immediately.

(2.) Keep the device in range of your router.
Make sure the device is placed close to the Wi-Fi router. If there has to be thick or insulated objects between the device and the
Wi-Fi router, which may lead to weak Wi-Fi signal, please make sure the Wi-Fi signal is in good level before you start using the device.

(3.) It is a delicated device with low power consumption design . Everytime the device is awakened and will work for few seconds.
After that, the device will enter standy mode to save power. You can set the work time in the app settings.

(4.) Because the mainland China does not receive Google's system push messages, you need to open the app's self-starting function in your phone to receive push messages.

(5.) This device provides one month of free cloud storage and face recognition services. If you need to continue using value-added services after the trial period expires, you need to purchase them in the app.

UBox

User Guide

The user guide is for reference only.
Screen shots displayed in this user’s guide
of the “UBOX” app may appear differently
than those currently featured in your app
as frequent updates and improvements.