



WARNING !!!

LEDIARY®

- ⚠ Turn off the electricity at the circuit breaker before installation.
Double check installation voltage is 110~130V AC with E26 Base.
Consult a licensed electrician if in doubt about the installation.
- ⚠ Turn off power to the fixture and allow the bulbs to cool before replacing.
Do not alter, re-locate or remove wiring.
- ⚠ Avoid exposing your eyes to the light bulb while it is on.
- ⚠ Don't expose to water though the BR30 bulb is damp rated.



Troubleshooting

PROBLEM	POSSIBLE CAUSE	CORRECTIVE ACTION
Bulbs not light	1. Bulb is burned out. 2. Power is off. 3. Voltage not right. 4. Loose wire connection.	1. Replace light bulb. 2. Make sure power supply is on. 3. Works between 110~130V AC. 4. Check the circuit connection.
Bulbs flicker	1. Bulb loose. 2. Improper dimmer setup 3. High wattage electrical appliance in the same circuit. 4. Incompatible dimmer. 5. Compatible dimmer but too many lights connected to one dimmer.	1. Tighten bulb firmly. 2. Double check the dimmer setting. 3. Turn off big wattage appliance or Separate from the same circuit. 4. Use the dimmer from recommended list. 5. Connect fewer lights to one dimmer.(Total light power under 75% of dimmer rated power)
Buzzing noise	1. Improper dimmer setup. 2. Incompatible dimmer. 3. Compatible dimmer but too many lights connected to one dimmer. 4. High wattage electrical appliance in the same circuit. 5. Incompatible circuit breaker.	1. Double check the dimmer setting. 2. Use the dimmer from recommended list. 3. Connect fewer lights to one dimmer.(Total light power under 75% of dimmer rated power) 4. Turn off big wattage appliance or Separate from the same circuit. 5. Mechanical circuit breaker: replace a compatible dimmer // Electronic control circuit breaker: replace the circuit breaker first.



Recommended Dimmers

LUTRON								
AY-600P	AYCL-153P	CN-600	D-603PH	DV-603PG	DV-600P	DVCL-153P	DVCL-153PL	GL-600H
GTJ-250M	MACL-153M	MA-600	TGCL-153P	LGCL-153PL	TG-600PHLH	TTCL-100H	TT-300	
LEVITON								
6613-P	6631	6633-P	6674	6672	6683	6684	IPI06	
Intertek		COOPER		LEGRAND				
DMS-S3-120N	DMD-LED3-120	9530WS	DLC03P	CDLV703-PW	D703-PTC	DLV703-PLA	HCL453PTCCCV6	



Contact Us

What the most effective way to solve problems is communication. So lediary store is bound to turn around things that bother you by 24-hour professional online service.

HOW TO CONTACT US:

1. Sign your Amazon account.


2.1 - Search the product about lediary, such as "lediary led lights"




OR 2.2. Click the **Orders** and open the order link you want to ask for help.



3. Go to the product page, and click blue font Sold by **lediary** on the right.



4. Click "Ask a Question" to send inquiry.



Customer Service

30-Days Full Refund Guarantee

If you are not completely satisfied or he item isn't what you expected, just tell us within 30 days. We will give you a full refund unconditionally.

Friendly Reminder

It's better to contact us than leaving negative shopping experience. Nothing is more important than your satisfaction and we will do our best to serve you.

Quick Response within 5 Hours

You could contact us without any hesitation at any time of the day, we won't reply you more than 5 hrs. (It's appreciate that you could provide us with video or pictures.) If emergency, please refer to the Troubleshooting on the back page.

5-year Warranty

We will send you brand new items for free or give you a full refund if quality problems happen in 5 years since the date of purchase.

Please rest assured that our service aim is to make customers 100% satisfied. If there is any problem, please contact us as soon as possible, we will not let you down.