



Any questions? Contact:
support@aisidra.net

Manufacturer
Shenzhen Zhonghantong Technology Co., Ltd
Address: Rm 1521, Ocean Bldg, 1050 Dongmen
North Rd Mutoulong Community, Cuizhu Street,
Luohu Dist, Shenzhen CHINA 518000



- ① LED Indicator
- ② Power Button
- ③ Transmitter Mode
- ④ Mode Switch
- ⑤ Receiver Mode
- ⑥ 3.5mm Audio Port
- ⑦ Micro USB Charging Port

Bluetooth® Profile	A2DP / AVRCP
Bluetooth Specification	Bluetooth 5.0
Audio Codec	TX: aptX™ low latency, aptX™, SBC RX: aptX™ low latency, aptX™, SBC, AAC
Range	33 ft / 10 m
Battery Capacity	160 mAh
Charging Power	5V DC
Working Hours	8-10hours
Charging Time	2hours
Operating temperature	-10 to 55 °C
Dimension (L x W x H)	1.88 x 1.39 x 0.43 in / 4.86 x 3.55 x 1.10 cm
Weight	0.53 oz / 15 g

Function	Operation
Power On	When off, press and hold the Power Button for 3 seconds
Power Off	When on, press and hold the Power Button for 3 seconds
Pairing	When powered on, press the Power Button twice to start pairing
Mode Switch	Slide the Mode Switch to and from TX and RX

Reconnect To A Connected Devices	Short Press Power button to reconnect to all connected device; if no connected after 12 seconds will auto in pairing mode
Clear Pair List	When off, switch from TX mode to RX mode, then turn it on, and the pairing list will be cleared.
Reset	When on, press power button and plug it into power source at the same time
Auto Power Off	Device will auto power off if battery lower than 3.1V
Low Battery Alarm	Device will have low battery alarm every 3 minutes if battery lower than 3.3V

LED Indicators	Status
Solid Red LED	Charging
LED Off	Fully charged
Flashing Red and Blue	Pairing
Flashing Red	Low battery
Solid Blue LED	Successfully paired
Flashing Blue	Powered on but not paired with Bluetooth® devices

Function	Operation
Power On	When off, press and hold the Power Button for 3 seconds
Power Off	When on, press and hold the Power Button for 3 seconds
Pairing	When powered on, press the Power Button twice to start pairing
Mode Switch	Slide the Mode Switch to and from TX and RX
Play / Pause	In RX mode, press the Power Button once to play / pause music
Reconnect To All Connected Devices	Short Press Power Button to reconnect to all connected device; if no connected after 12 seconds, will auto in pairing mode
Auto Power Off	Device will auto power off if battery lower than 3.1V
Low Battery Alarm	Device will have low battery alarm every 3 minutes if battery lower than 3.3V

LED Indicators	Status
Solid Red LED	Charging
LED Off	Fully charged
Flashing Red and Blue	Pairing
Flashing Red	Low battery
Solid Blue LED	Successfully paired

1. Connect the micro-USB end of the cable to the charging port of the Bluetooth adapter.
2. Plug the USB end of the charging cable to a USB charging port or any active USB port.
3. LED indicator will turn red when charging and will automatically turn off when fully charged.

- You can use the adapter while it is charging.
- We recommend charging the unit for at least 2 hours before using it for the first time.

Pair in TX mode:

1. Set Aisdia AD-BA010 to TX mode and connect it to the AUDIO OUTPUT jack of your non-Bluetooth devices such as TV/PC/MP3 player.
2. Place your Bluetooth audio receiving device such as Bluetooth headphones/speaker within 3 feet / 1 meter and set it to pairing mode.
3. Press and hold the Power Button for 5 seconds and tap twice to enter pairing mode (blinking red and blue). Within a few seconds, both devices will pair to each other and the transmitter will stay solid blue.

1. Make sure the adapter is set into TX mode, both devices are within 3ft to each other;
2. Find the circular button on the rear side of the charging case of your AirPods;
3. Open the lid of your AirPods charging case (do not remove AirPods from the case)

EN 06

4. Tap and hold the circular button until the light inside the case blinks white;
5. Turn on the adapter and it will automatically enter pairing mode (blinking red and blue);
6. Both devices will search for each other and connect to each other within seconds. The transmitter will stay solid blue while the AirPods charging case will turn into green light once connected.

Press and hold the Power Button of the adapter for 3 seconds, it will start pairing.

1. Activate the Bluetooth function on your phone and search for the nearby Bluetooth devices:
 - For iOS: Settings > Bluetooth > On
 - For Android: Settings > Wireless & Networks > Bluetooth: On > Scan for devices
2. Find "AD-BA010" in the search results and tap on it to connect. Once connected, the LED indicator will turn solid blue.

- The adapter enters pairing mode automatically when powered on for the first time.
- The original pairing method in TX mode will be cleared after a power switch, the RX mode will not. It will automatically start pairing each time when powered on.
- If a PIN code is required for pairing, try 0000,8888,1111 or 1234.
- The adapter can remember two recently paired devices and will attempt to pair with devices automatically, without going into pairing mode.
- Please do not turn on the adapter right after it is turned off, otherwise the adapter might crash and the battery will be damaged.
- If the adapter fails to pair with your devices, please kindly clear the pairing history of both devices and try to re-pair them following the pairing steps.
- If the adapter is used in RX mode, it also requires to support APX Low Latency Code to run low latency mode; otherwise, the receiving device might use other code (e.g. the

SBC, aptX), which might result in a 70-200ms audio delay that might be noticeable to some users.

in TX mode:
The adapter is able to pair with two Bluetooth® stereo
earphones/speakers at the same time.

1. Follow the previous instructions in the "Pairing" section to pair the AD-BA010 with your first device.
2. Turn off the Bluetooth® function on your first device, tap the Power Button twice to pair and connect to your second device.
3. Turn on the Bluetooth® function on your first device. In approximately 12 seconds, the first device will automatically connect in.

- When you pair with two devices, both can play music at the same time.
- The adapter will automatically re-pair when powered on.

The adapter is able to pair with two Bluetooth® devices at the same time.

1. Follow previous instructions in the "Pairing" section to pair the AD-BA010 with your first device, **Disable the Bluetooth® function** on your first device, Tap the Power Button twice to pair with the second device.
2. Turn on the Bluetooth® of the first device, now AD-BA010 adapter is successfully paired with both two devices.

Only one device can play music at any time. You have to stop the music on one device to play on the other.
The adapter will automatically re-pair when powered on.

- Keep the adapter away from heat and humidity.
- Do not expose the adapter to direct sunlight or extreme heat.
- Do not try to take the adapter apart. It may cause serious damage.
- Do not drop or knock the adapter on hard surfaces as it damages the interior circuit.
- Do not use chemicals or detergents to clean the product.
- Do not scrape the surface with sharp objects.

This product is covered with Aisidra product and labor warranty for 12 months from the date of its original purchase.

EN 09

